

Putco Luminix Light Bar 4-Button Wireless Remote Instructions

Congratulations on your purchase of a high quality PUTCO product.
Should you need any application or technical assistance,
feel free to call us at: 1-800-247-3974
Monday-Friday 8:00 a.m. - 5:00 p.m. (Central Standard Time)
Contact your PUTCO dealer for other quality accessories.

SPECIFICATIONS:

Range: 30 feet open air Input Voltage: 10-30 VDC Max Current: 25 Amps

Remote Battery: 27A 12V alkaline battery

Compatible with: Luminix, Hornet, Blade, WorkBlade and Freedom Blade products.





BLACK: Connect to constant battery negative.

(-)

RED: Connect to constant battery positive. (+)

BLUE: Normally open. Connects to positive red wire when button A is pressed.

GREEN: Normally open. Momentarily connected to the ground/negative black wire when button D is pushed.

ORANGE: Normally open. Momentarily connected to the ground/negative black wire when button B is pushed.

GREY: Normally open. Momentarily connected to the ground/negative black wire when button C is pushed.

For other quality lights and lighting accessories, visit

www.Putco.com